

"Express Mail" mailing label number EL 465783435US

Date of Deposit 9/20/01

I hereby certify that this paper or fee is being deposited with the United States Postal Service

"Express Mail Post Office to Addressee" services under 37 C.F.R. 1.10 on the date indicated above

and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.

Typed Name of Person Mailing Paper or Fee: Nicole Nielsen

Signature: Nicole J. Nielsen

PATENT APPLICATION

DOCKET NO. 10004333-1

EL 465783435

Methods of Optical Communication and Optical Communication Systems

INVENTOR:

Kent W. Carey
1121 Fife Avenue
Palo Alto CA 94301

Methods of Optical Communication and Optical Communication Systems

TECHNICAL FIELD

- [0001] The invention relates to methods of optical communication and optical communication systems.

BACKGROUND OF THE INVENTION

- [0002] The amount of information communicated within networks, such as voice and data networks, has increased dramatically in recent years. Accordingly, such has resulted in demands for increased bandwidth in networks to communicate more information at increased rates of data transfer. As the demands for bandwidth of data communications continues to increase, improved devices and methodologies to accommodate the demands are desired.
- [0003] One example of data transmission technology uses low power, high data rate and wavelength division multiplexing to achieve high bit rate data transmission. An exemplary implementation utilizes a relatively large number of optical sources at different wavelengths. However, such configurations can be relatively difficult to fabricate and relatively expensive to package.
- [0004] Another solution has been to directly modulate light sources, such as laser diodes. However, the rate of modulation within such systems is less than desirable to accommodate the increasing bandwidth demands.
- [0005] More specifically, conventional fiber optic communications systems typically rely on a separate source for each optical wavelength used in a wavelength division multiplexed system. However, as more and more optical wavelengths are used, larger

[0006] Accordingly, there exists a need for an improved approach to generating frequency multiplexed optical signals.

[0007] Aspects of the present invention provide for multiplexing individually modulated components of a source light. A broad-spectrum light source provides the source light; an optical divider divides the source light into plural carrier beams. A multi-channel modulator modulates each carrier beam responsive to a respective data signal to yield a respective encoded beam. An optical combiner multiplexes the encoded beams. The optical combiner can also inject the multiplexed signal into a communication medium for reception elsewhere.

S:\AG5\011\PO4.wpd A270109101113AM

[0009] According to additional exemplary aspects, optical modulators pass a desired portion of a received optical signal having at least one predefined wavelength. The modulators optically modulate the desired portion of the optical signal having the at least one predefined wavelength responsive to a respective data signal.

[0010] Additional aspects of the invention disclose methods which include passing a plurality of desired portions of an optical signal using a plurality of respective optical modulators. The desired portions of the signal individually have at least one predefined wavelength. The method also includes optically modulating the desired portions of the optical signal using the respective optical modulators responsive to data signals. In one exemplary implementation, the optically modulating is implemented using frequency modulation.

[0011] As is apparent from the foregoing, the present invention has both method and structural aspects. By using a single broadband light source for the multiple components of a multiplexed signal, the present invention overcomes many of the problems faced by prior art systems that use multiple light sources. It much easier and more cost-effective to manufacture a single broad-spectrum light source than multiple single-frequency light sources. Furthermore, more channels can be implemented without encountering heat-dissipation limits. Also, since the light source is not modulated, switching speed limitations associated with modulating a light source directly are not encountered. More specifically, aspects of the invention disclose arrangements and methodologies wherein signal bandwidths are limited by the response of the modulator which can be much faster than the

096175-09001

096175-09001

- 096175-00001

096175-00001

- 096175-09001

[0019] The light of broad spectrum optical signal 21 is provided to an optical divider 22. Optical divider 22 divides the light of the broad spectrum optical signal 21 into a plurality of optical signals 23, also referred to as carrier light-beams. In exemplary arrangements, optical divider 22 is configured as a beam splitter, array waveguide (AWG), prism or other wavelength dispersive element.

[0021] According to aspects of the invention, the number of channels within optical communication system 10 is determined by the number of optical signals 23 outputted from optical divider 22. According to one exemplary embodiment of the present invention, individual channels correspond to respective different wavelengths of optical signal 21. The number of optical signals 23 generated by optical divider 22 may be varied according to the desired implementation of optical communication system 10.

S:\AG5\011\PO4.wpd A270109101113AM

modulators (exemplary optical modulators are described below with respect to references 34, 34a, 34b, 34c illustrated in Figs. 3 and 4). Such optical modulators within array 24 are individually configured to pass a desired portion of the optical signal 21 and to optically modulate the desired portion of the optical signal 21 for encoding data thereon. In the embodiment illustrated in Fig. 1, desired portions of optical signal 21 correspond to respective optical signals 23 as described in further detail below.

[0023] According to aspects of the present invention, optical modulators of array 24 are configured to implement frequency modulation of the respective desired portions of optical signal 21. Alternatively, amplitude modulation or other modulation schemes may be utilized to encode data upon the portions 23 of optical signal 21.

[0024] Depending upon the configuration of optical communication system 10 shown in Fig. 1 or provided in other arrangements, optical modulators of array 24 also operate to filter undesired portions of optical signal 21 or optical signals 23. Individual optical modulators of optical modulator array 24 have passbands configured to pass and to modulate light within a desired portion (passing light having one or more predefined wavelength) and to filter light within undesired portions (at other wavelengths outside of the respective passbands of the optical modulators). For example, optical modulators of optical modulator array 24 are individually configured to pass and modulate a portion of optical signal 21 within the respective passband and to not pass or modulate portions of optical signal 21 outside of the respective passband. In an exemplary arrangement, one or more of the optical modulators is configured to pass one or more wavelength

of light different than at least one wavelength of light passed by the others of the optical modulators.

[0025] The optical modulators of array 24 are configured to provide appropriate spacing of the desired portions of optical signal 21 from one another. Passbands of the optical modulators are separated by appropriate guard bands to avoid cross-talk or other interference between channels in one embodiment.

[0026] In the described optical communication system 10 depicted in Fig. 1, optical signals 23 are provided to respective optical modulators of modulator array 24. Desired portions of the optical signal 21 to be passed and modulated within the respective optical modulators may be substantially provided as respective optical signals 23 as determined within divider 22 and corresponding to the respective passbands of the optical modulators leaving minimal or no filtering of light of the optical signals 23. In such an arrangement, optical divider 22 is configured to divide the optical signal 21 into optical signals 23 substantially comprising the desired portions having wavelengths of light corresponding to the passbands of the respective optical modulators. Alternatively, filtering of light from individual optical signals 23 is implemented by the optical modulators to remove undesired light from optical signals 23. Optical signals modulated and outputted from modulator array 24 have reference 25 in Fig. 1.

[0027] In an alternative implementation of optical communication system 10, divider 22 provides no wavelength division but rather divides optical signal 21 into optical signals 23 which individually have substantially the same wavelength spectrum as signal 21. Accordingly, optical signals 23 comprise broad spectrum signals in such an embodiment. Optical modulators of array 24 filter and

modulate the broad spectrum signals 23 providing optical signals 25 as described above. In such an arrangement, the optical modulators are configured to filter undesired portions of optical signals 23 outside of the respective passbands of the optical modulators and to pass and to modulate the respective desired portions of optical signals 23.

[0028] Data source(s) 12 are configured to provide a plurality of data signals 13 containing information to be communicated within optical communication system 10. Data source(s) 12 are arranged in the described embodiment to provide a plurality of data signals 13 corresponding to the channels within optical communication system 10. For example, the number of data signals 13 corresponds to the number of optical signals 23, 25 within optical communication system 10. The data signals 13 are utilized to modulate the desired portions of optical signal 21 to form optical signals 25. At any given time, one or more of the channels may not be utilized. Other embodiments are possible.

[0029] Data source 12 outputs the data signals 13 comprising electrical signals. Exemplary data signals 13 individually have a frequency utilized to control modulation of desired portions of the optical signal 21 using optical modulators of array 24. Exemplary data signals 13 have MHz or GHz frequencies, with the higher frequencies, such as 1-100 GHz for example, providing increased bandwidth compared with the lower frequency signals.

[0030] The optical modulators of array 24 have respective filter frequencies. The filter frequencies of the optical modulators of array 24 are different in one exemplary embodiment to provide different communication channels of optical communication systems 10. The passbands of the respective optical modulators

of array 24 are designed to be electronically tunable as described below. Accordingly, data signals 13 are utilized to control the electronic tuning of the respective optical modulators 34 to encode the data upon the respective desired portions of optical signal 21 by modulating the filter frequencies and passbands of the respective optical modulators 34 at the data rates of data signals 13.

[0031] Modulator array 24 outputs the plurality of modulated desired portions as optical signals 25, also referred to as encoded light-beams, to combiner 26. Combiner 26 is configured to receive the desired modulated optical signals 25 and to combine such signals 25 into an optical signal 27, also referred to as a multiplexed-light beam in at least one embodiment, for communication using optical communication medium 28. In one configuration, combiner 26 is configured to frequency multiplex signals 25 to combine signals 25.

[0032] Optical communication medium 28 is implemented in any desired configuration configured to communicate one or more optical signal. Exemplary optical communication media include an optical waveguide comprising one or more optical fiber, air or other appropriate optical transmission medium.

[0033] Other arrangements of optical communication system are possible in addition to those described with reference to Fig. 1.

[0034] Referring to Fig. 2, one exemplary implementation of optical communication system 10 of Fig. 1 is depicted. Light source 20 is configured as an edge emitting light emitting diode 30 coupled with optical divider 22 implemented as an array waveguide 32. Optical modulator array 24 is coupled with array waveguide 30. Although not shown in Fig. 2, data source 12 supplies desired data

signals to optical modulator array 24. Optical combiner 26 is coupled intermediate optical modulator array 24 and optical communication medium 28. Optical communication medium 28 is implemented as a single optical fiber 28 configured to communicate the modulated desired portions of optical signal 21 outputted from array 24 and combined in combiner 26.

[0035] Decoding of communication data can be accomplished by one or more standard technique. For example, one decoding technique includes demultiplexing the optical signals at different wavelengths into separate channels and then converting frequency modulation to intensity modulation which can be monitored with an optical detector. Other decoding arrangements may be used.

[0036] Referring to Figs. 3 and 4, an exemplary configuration of optical modulator array 24 is depicted. Modulator 24 comprises a plurality of modulators 34, 34a, 34b, 34c in the depicted embodiment corresponding to four communication channels within optical communication system 10. More or less channels are provided according to other optical communication systems and methodologies of the present invention.

[0037] The depicted modulators 34, 34a, 34b, 34c are configured as Fabry-Perot cavities in the described embodiment. Modulators 34, 34a, 34b, 34c are tuned to one or more respective wavelength (i.e., passbands) and are configured to modulate desired portions of optical signal 21 having the respective wavelengths. As described above, modulators 34, 34a, 34b, 34c pass and modulate portions of optical signal 21 within the respective passbands of the modulators. If wavelengths of light outside of the respective pass bands are provided to modulators 34, 34a, 34b, 34c, such light is filtered and not passed according to the exemplary arrangement.

[0038] Individual modulators 34, 34a, 34b, 34c include a respective one of cavities 42, 42a, 42b, 42c, electrodes 44, 46, insulators 48 and mirrors 50 as shown. Modulators 34, 34a, 34b, 34c are provided upon a substrate 40 which is transparent to wavelengths of light to be communicated within optical communication system 10 in the described exemplary embodiment. An exemplary substrate 40 comprises silicon. Insulators 48 are provided intermediate electrodes 46 and cavities 42, 42a, 42b, 42c as illustrated and comprise silicon in one example.

[0039] Referring specifically to Fig. 4, mirrors 50 are provided upon upper and lower portions of respective cavities 42, 42a, 42b, 42c. Exemplary mirrors 50 in one instance comprise high reflectivity mirrors, such as Bragg mirrors, comprising two or more even number of layers of transparent material having different refractive indices, such as silicon dioxide, titanium oxide or silicon nitride, for example.

[0040] In the described embodiment, light from optical signal 21 is received within the upper surfaces of cavities 42, 42a, 42b, 42c and passed through the lower surfaces of the respective cavities and through substrate 40 for application to combiner 26 illustrated in Fig. 1.

[0041] Respective data signals 13 (not shown in Figs. 3 and 4) are provided to electrodes 44, 46 to electronically tune respective cavities 42, 42a, 42b, 42c. Optical path lengths of the modulators 34, 34a, 34b, 34c dictate the frequencies of the respective passbands of the respective modulators. The optical path lengths of modulators 34, 34a, 34b, 34c, are defined by the physical length and refractive indices of cavities 42, 42a, 42b, 42c. Varying the physical length and/or refractive indices varies the

passband of the respective modulator 34, 34a, 34b, 34c .

[0042] In the described exemplary embodiment, the respective cavities 42, 42a, 42b, 42c have different physical lengths, as illustrated, tuned to the desired portions of optical signal 21 to be passed and modulated. In the described embodiment, cavities 42, 42a, 42b, 42c contain a material having a relatively high electro-optic coefficient. Exemplary materials include electrically controllable birefringent material, such as lithiumniobate, barium titanate or other materials including polymer materials having high electro-optic coefficients. Cavities 42, 42a, 42b, 42c contain the same or different birefringent material depending upon the configuration of array 24 and frequencies of light to be modulated.

[0043] The material(s) within cavities 42, 42a, 42b, 42c may be varied to further tune optical modulators 32, 32a, 32b, 32c to the desired passbands. In such an arrangement, the physical length of cavities 42, 42a, 42b, 42 may be held constant or varied depending upon the desired configuration and desired passbands. In general, the effective cavity length may be shorter if distributed Bragg mirrors are utilized as mirrors 50 inasmuch as mirror thickness can be a reasonable fraction of overall cavity length.

[0044] Data signals 13 applied to the electrodes 44, 46 vary the refractive indices of the birefringent material in cavities 42, 42a, 42b, 42c providing modulation of the filter frequencies of modulators 34, 34a, 34b, 34c and modulation of the desired portions of optical signal 21 passing therethrough. The wavelengths or frequencies of the desired portions of the optical signal 21 are modulated within modulators 34, 34a, 34b, 34c responsive to the varying of the refractive indices of materials within cavities 42, 42a, 42b, 42c.

[0045] As described, the present invention provides improved devices and methods for encoding data on an optical signal. In one example of the invention, frequency modulation obtained by modulation of a filter illuminated with a broadband source provides signal bandwidths which are limited by the response of the tunable filter which can be much faster than the bandwidth of a laser which is limited by capacitance and carrier dynamics. Accordingly, aspects of the invention provide usage of a bright, broad spectrum incoherent optical source together with high speed tunable filters to achieve high data rate transmission over a broad range of operating temperatures. Other aspects are provided as described above.